



# **Features**

- Up to 4W CW output power.
- High Quality, Reliability,
  - & Performance

# Applications

- Fiber Lasers
- Material Processing
- Graphics
- Medical
- Defense

High brightness, high quality, and high reliability are the foundation of our multi mode product line. Sheaumann's 940nm multi mode laser diodes are available with up to 4W of continuous output power from a single 200um emitter chip. Sheaumann's trademark laser chip design creates un-measurable degradation and long lifetimes that make our chips among the most reliable in the industry today. Our 940nm multi mode line serves a broad range of applications including fiber lasers, material processing, graphics, medical, and defense.

Packaging options include industry standard 9mm TO-can, C-mount, B-mount, and QA-mount. More product options are available upon request. Please view our website for mechanical drawings of all of our sub-mounts.

		 <u>4W Series</u>		
Parameter	Unit	Min	Тур	<u>Max</u>
Wavelength	nm	935	940	945
Spectrum FWHM	nm	-	3	5
Operating Power (P <sub>o</sub> )	w	-	4.0	-
Operating Current (I <sub>o</sub> )	А	-	4.4	5.0
Operating Voltage (V <sub>o</sub> )	v	-	1.7	2.0
Lifetime	hour	20,000	-	-
Vertical Far Field	deg, FWHM	-	30	35
Parallel Far Field	deg, FWHM	-	8	10
Threshold (I <sub>th</sub> )	A	-	0.5	0.8
Slope Efficiency (dP/dI)	W/A	0.8	0.9	-
Storage Temp.	۰C	-40	-	80
Operating Temp. (T <sub>op</sub> )	۰C	-20	25	50
Lead Soldering Temp.(5 sec)	۰C	-	-	250

# Standard Product Specifications for 940nm Multi-mode Diodes

**Product Specifications** 

940nm Multi-Mode Laser

Diodes (200um)

**Description:** 

Note:

1) Specifications are subject to change without notice.

2) All Sheaumann Laser products are TE polarized



1

### France

Laser Components S.A.S. Tel: +33 1 39 59 52 25 Fax: +33 1 39 59 53 50 info@lasercomponents.fr www.lasercomponents.fr

### United Kingdom

Laser Components (UK) Ltd. Tel: +44 1245 491 499 Fax: +44 1245 491 801 info@lasercomponents.co.uk www.lasercomponents.co.uk

# Nordic Countries

Laser Components Nordic AB Tel: +46 31 703 71 73 Fax: +46 31 703 71 01 info@lasercomponents.se www.lasercomponents.se



<b>Determining</b>	Your Product number:	MM—WWW	—PPPP—XYZ—(custom add-ons)	Standard Product Configurations					
(package)-{wavelength)-{power}-{options}									
Package:		X Option (aperture size)		CM-940-4000-250					
СМ	C-mount	2	200µm aperture	BM-940-4000-250					
BM	B-mount	Y Option (wavelength tolerance)		QA-940-4000-250					
QM	Q-mount	5	±5 nm	C4-940-4000-250					
C4	chip on 4mm submount	Z Option (additional options)							
Wavelength:		0	none						
940	940nm								
<u>Power Options:</u> 4000	4W	Please note: These are our standard product configurations. Other options may be available, please inquire about any additional options that you may require when contacting our Sales Team.							

#### <u>Safety</u>

Caution: Laser light emitted from any diode laser is invisible and may be harmful to the human eye. Avoid looking directly into the diode laser aperture when the device is in operation.

**Note:** The use of optical instruments with this product will increase eye hazard.

#### **Operating Considerations**

Operating the diode laser outside of its maximum ratings may cause device failure or a safety hazard. Power supplies used with the component must be employed such that the maximum peak optical power cannot be exceeded. CW diode lasers may be damaged by excessive drive current or switching transients. When using power supplies, the diode laser should be connected with the main power on and the output voltage at zero. The current should be increased slowly while monitoring the diode laser output power and the drive current. Device degradation accelerates with increased temperature, and therefore careful attention to minimize the case temperature is advised. A proper heat-sink for the diode laser on a thermal radiator will greatly enhance laser life.

ESD Caution

### Power Output Danger Label









# 21 CFR 1040.10 Compliance

Always handle diode lasers with extreme care to prevent electrostatic discharge,

the primary cause of unexpected diode failure. You can prevent ESD by always wearing wrist straps, grounding all applicable work surfaces, and following

extremely rigorous anti-static techniques when handling diode lasers.

Because of the small size of these devices, each of the labels shown are attached to the individual shipping container. They are illustrated here to comply with 21 CFR 1040.10 as applicable under the Radiation Control for Health and Safety Act of 1968.

### Germany & Other Countries Laser Components GmbH Tel: +49 8142 2864 - 0 Fax: +49 8142 2864 - 11 info@lasercomponents.com www.lasercomponents.com

#### France

Laser Components S.A.S. Tel: +33 1 39 59 52 25 Fax: +33 1 39 59 53 50 info@lasercomponents.fr www.lasercomponents.fr

### United Kingdom

Laser Components (UK) Ltd. Tel: +44 1245 491 499 Fax: +44 1245 491 801 info@lasercomponents.co.uk www.lasercomponents.co.uk

# Nordic Countries

Laser Components Nordic AB Tel: +46 31 703 71 73 Fax: +46 31 703 71 01 info@lasercomponents.se www.lasercomponents.se